



The **Multiverse® Transmitter** opens a new world in wireless DMX/RDM. Its Ethernet input allows it to take in Streaming ACN (sACN) or Art-Net and to transmit between eight and 10 user-selectable universes of DMX/RDM, depending on the type of Multiverse Transmitter product used, with the ability to use less radio energy than a present-day single universe wireless DMX transmitter.

The **Multiverse Transmitter** has a Bluetooth radio receiver built in that allows it to communicate with City Theatrical's multi award winning DMXcat® app from the user's smartphone. This gives the user smartphone control of any lighting fixture that is part of the Multiverse setup, whether it is a lighting fixture with a Multiverse Module inside, a lighting fixture receiving its data from a Multiverse Node, or any wired fixture downstream of those devices.

The **Multiverse Transmitter** is Wi-Fi enabled, allowing for communication and control from tablet-based Wi-Fi lighting controllers like Luminair.



Pipe Mount

SPECIFICATIONS:

P/N	Frequency	Universes
5910 (Shown)	900MHz/2.4GHz	9
5911	2.4GHz (x2)	10
5912	900MHz (x2)	8

Physical

Length	196.9mm	(7.75 in)
Width	101.5mm	(4.0 in)
Height	47mm	(1.85 in)
Antenna	3dBi	
User Interface	DMXcat app	
Construction	Die Cast Aluminum	
Power Connector	5.5 x 2.1mm, powerCON TRUE1 in/trhu, RJ-45	

Electrical

Power	100-240VAC 50/60Hz, 5-30VDC, POE Class 0, 5W	
Broadcast Power	3.2mW, 10mW, 32mW, 100mW	
Broadcast Modes	Adaptive, Full, Low, Mid, High, Max	
DMX Burst Modes	Auto Dynamic	
Ethernet Protocols	802.11 bgn, 10BASE-T sACN, Art-Net	
Hopping Patterns	17	
SHoW IDs	Multiverse: 216 (Americas), 176 (World); Neo: 70	
RF Sensitivity	-95dBm	
RDM Features	RDM Proxy, RDM Responder	

Product Information

Use Environment	Indoor
IP Rating	IP30
Compliance	FCC, IC, CE, ETL
Warranty	One year



What's in the box