



With tens of thousands of units sold since their introduction in 2011, SHoW Baby plug and play transceivers set the standard for ease of use and reliability at an affordable price point. The addition of Multiverse radio technology enhances the performance even more.

Multiverse® SHoW Baby™ is a wireless DMX transceiver that delivers breakthrough plug and play wireless DMX and RDM transmission. In its default mode, it works like all other SHoW Baby Transceivers with six user selectable SHoW IDs.

By connecting an RDM controller, like DMXcat® Multi Function Test Tool, all of the revolutionary new 2.4GHz Multiverse SHoW IDs are accessible. Users can add to their existing SHoW Baby systems, build new single universe Multiverse systems, or use **Multiverse SHoW Baby** as a receiver on multiple universe systems with a Multiverse Transmitter.



Set SHoW IDs on the back of the unit

SPECIFICATIONS:

P/N	Frequency	Universes
5900	2.4GHz	1

Physical		
Length	92mm	(3.625 in)
Width	76mm	(3.0 in)
Height	46mm	(1.8 in)
Antenna	2dBi	
User Interface	One Button/Indicator Lights	
Construction	Injection Molded Plastic	
Power Connector	5.5mm x 2.1mm	

Electrical	
Power	5-30VDC, 1W
Broadcast Power	2.5mW, 8mW, 25mW, 80mW
Broadcast Modes	Adaptive, Full, Low, Mid, High, Max
DMX Burst Modes	Auto Dynamic
Ethernet Protocols	N/A
Hopping Patterns	3
SHoW IDs	Multiverse: 176; Neo: 70
RF Sensitivity	-95dBm
RDM Features	RDM Proxy, RDM Responder

Product Information	
Use Environment	Indoor
IP Rating	IP20
Compliance	FCC, IC, CE
Warranty	One year



What's in the box